

**ONEAC FA Series Three Phase Filters:** Sensitive electronic equipment in industrial, medical and telecom applications often require protection from the disruptive effects of ongoing power line noise. ONEAC FA Series filter products provide cost-effective protection from damaging signals.

#### High current equipment requires cost-effective solutions.

Three phase or high current equipment, critical to the operation of industrial, medical or telecom systems are driven by power sources that propagate voltage transients and electrical noise. Although there may be a step-down or isolation transformer somewhere within the power feed, troublesome power line noise may still jeopardize the trouble-free operation of necessary equipment.

Heat treating ovens, robotic controllers and CNC machines are typical industrial applications where power protection can improve reliability. Likewise, MRI equipment, CATSCAN equipment and linear accelerators in the medical industry and large PBX installations in the telecom industry can benefit from the assurance of clean power.

#### Significantly reduce problems caused by electrical noise

The FA Series high-performance filter provides a cost-effective solution for three phase, single or split phase applications from 30 to 200 amps. A bi-directional circuit provides susceptibility and emissions protection to prevent key equipment from the impact of power line problems. And it prevents noise generated by large equipment from effecting critical systems nearby.

#### Robust design, proven durability

Designed and manufactured under ISO 9001 quality procedures, ONEAC FA Series' last far longer than surge suppressors and are highly reliable—even in harsh electrical environments. Their exceptionally high mean time between failure (MTBF) backs that up. So do we with a 5-year warranty and a willingness and ability to engineer site-specific protection schemes that eliminate your power problems entirely.



- **Tight surge let-through:** provides industrial level protection against high voltage spikes.
- **High frequency noise filters:** exceeds insertion loss capability of standard industrial filters to provide maximum attenuation of high frequency noise.
- **Broad voltage capabilities:** models for input voltage of 190V through 600V meet North American and international applications.
- **Premium grade filtering:** significantly reduced downtime and improved equipment productivity.
- **Convenient installation:** packaged within a NEMA 12 enclosure, the FA Series is wall or floor mountable.
- **Unmatched factory support:** every unit in the FA Series is designed and manufactured in the US and backed by ONEAC's five-year warranty.

## ONEAC FA Series Three Phase Filters: Specifications

### RFQ Insertion Loss (line to lead and lead to line)

FA Series	400 kHz to 4 MHz — 45 dB typical
	100 kHz to 10 MHz — 35 dB typical
	30 kHz to 30 MHz — 35 dB typical

### Approvals

UL, CSA approved. (CE on select models.)

### Warranty

ONEAC's high degree of quality is backed by a five-year warranty.

### Performance Characteristics

**Surge voltage withstand capability:** ANSI/IEEE C62.41 Category A&B, 6 kV/200 & 500 Amp, 100 kHz ringwave and 6kV/3000A impulse

**Surge and Noise Rejection-Isolation:** with unit under power, and ANSI/IEEE C62.41 Category A pulse applied either normal mode (L-N) or common mode (N-G) at the input, the noise output voltage will be less than 20V normal mode and common mode in all four quadrants using a Keytek 711A/J (or equivalent) surge generator and a low-voltage, high sensitivity probe.

**Load Power Factor:** 0.3 leading to 0.3 lagging

**Load Regulation Response Time:** <2 msec for 50% change in load

**Interruption Response Time:** output voltage will track input voltage in less than 2 msec at power-off and power-on for a single-cycle asynchronous notch

**Distortion:** <1% THD added into a resistive load

**Overload Protection:** fuse

**Cooling:** convection

**Input/Output Connectors:** Hardwired


**Normal & Common Mode Clamping Response Time:** instantaneous

**Ambient Operation:** 10,000 ft. (3,000 meters) max elevation, 0-95% humidity non-condensing, 32-104°F (0-40°C) convection

MODELS*	FA23030	FA63030	FA23060	FA63060	FA23100	FA63100	FA23200	FA63200
Load Current Rating (Amps)*	30/φ	30/φ	60/φ	60/φ	100/φ	100/φ	200/φ	200/φ
Input/Output Voltage Range, WYE (VAC)	190/110 to 250/144	380/220 to 600/346	190/110 to 250/144	380/220 to 600/346	190/110 to 250/144	380/220 to 600/346	190/110 to 250/144	500/288 to 600/346
Input/Output Voltage Range, DELTA (VAC)	190 to 250	380 to 600	190 to 250	380 to 600	190 to 250	380 to 600	190 to 250	500 to 600
Surge Current (Amps) 10 sec. typical	150	150	300	300	500	500	1000	1000
1kHz Forward Transfer Impedance (Ohms)	<1	<1	<1	<1	<1	<1	<1	<1
Efficiency at Rated Output (%)	>98	>98	>98	>98	>98	>98	>98	>98
Enclosure Rating**	NEMA 12	NEMA 12	NEMA 12	NEMA 12	NEMA 12	NEMA 12	NEMA 12	NEMA 12
Maximum dimensions (W) in.	16	16	20	20	24	24	30	30
Maximum dimensions (H) in.	24	24	30	30	30	30	36	41
Maximum dimensions (D) in.	9	9	9	9	13	13	17	17
Shipping weight— lbs.	85	85	150	150	210	210	365	455
Part Number	026-005	026-075	026-060	026-076	026-070	026-077	026-011	026-078

\* specified at 25°C derate 1% per ambient °C to a maximum of -15% at 40°C

\*\*NEMA 12 -- drip and dust tight, NEMA 12 equivalent to IP55 (IEC 529 type)



All ONEAC-manufactured products are Y2K compliant.

ONEAC is a trademark of ONEAC Corporation. All other trademarks, product and corporate names are the property of their respective owners.



ONEAC is a UL/BSI registered corporation — Certification No. A2900



(800) 327 8801 EXT. 2 in USA AND CANADA

27944 N. Bradley Road, Libertyville, IL 60048 Phone 847 816-6000 FAX 847 680-5124

+44 (0) 1235 534721 in UK AND EUROPE

18 & 20 Blacklands Way, Abingdon Business Park, Abingdon, Oxfordshire OX14 1DY, UK FAX +44 0 1235 534197